

GENERATOR SPECIFICATION	
Voltage	230/115
Phase	1
Frequency	50Hz
Prime Power (PRP)	2.7 kVA / 2.2 kW
Alternator	NSM K80B
Alternator Type	Brushless - Smooth Waveform
Fuel tank capacity	3.1 Litres
Autonomy 75% load	3.1 Hours
LWA	94
dBA @ 7M	69

ENGINE SPECIFICATION	
Engine	Honda GX160
Emissions certified	EU Stage V
Cylinders	Single
Distribution	O.H.V.
Aspiration	Naturally aspirated
Cooling	Air
Displacement	163 cm <sup>3</sup>
Rpm	3000
Starting system	Recoil
Fuel	Unleaded 86 octane or higher



DIMENSIONS (mm)			WEIGHT (KG)
Length	Width	Height	
610	420	415	35



### CONTROL BOX

- 1 x 16A 230V & 1 x 16A 115V BS4343 sockets.
- Reset circuit breaker overload protection.
- Voltage selector switch.

### STANDARD FEATURES

- Robust metal control box.
- Oil alert/low oil shutdown.
- 3 Year engine warranty (Limited).
- Full wrap-around frame.
- Brushless smooth waveform alternator.

### OPTIONS

- AVR (Automatic Voltage Regulator).
- LPG conversion.
- Electric start.
- Long run tank (plastic).
- Single voltage.
- Trolley kit.



\* Different model used to illustrate trolley option.

### POWER DEFINITION

#### Prime Power (PRP) :

Applicable for supplying power to varying electrical load for unlimited hours in accordance ISO 8528-1.