





Product Code:  82001I-E
 82001I-E-EU

Noise Level: 53 dBA @ 7m

Max AC output: 2000 Watts

Running Watts: 1600 Watts

Warranty: 3 Year

Suitable for:

- ✓ Computers
- ✓ Small appliances
- ✓ Household items



Optional ParaLINK Parallel Kit



Description

Lightweight power and clever design are yours with the Champion 2000-watt stackable inverter generator. Rely on the 80cc engine and enjoy a quiet 53 dBA for up to 11 hours of run time. The optional ParaLINK Parallel Kit with RV Ready outlet and 30 amps of power doubles your output and saves space.

Champion's innovative EZ Start Dial takes the confusion out of starting an engine with easy access to all the controls you need, plus Cold Start Technology ensures a quick start in cold weather.

The easy to read Digital LED Display includes maintenance, low oil and receptacle status indicators and monitors power output, total run time, fuel level and fuel life.

Champion minimizes the hassle of refueling in the dark with Fuel Fill Assist LED, a cleverly designed push-button LED built right into the handle to illuminate the petrol fill area.

**Please note the image shown may differ slightly depending on UK/EU model.*

Features

- 2000 Max Watts
- 1600 Running Watts
- EZ Start Dial
- Stackable
- Ultra Quiet at only 53 dBA
- Digital LED display
- True sine wave inverter technology
- Economy mode to save fuel
- Dual Port (2.1A/1A) USB Adapter (Included)
- Parallel Connectable

Includes:

- Oil funnel
- Dual USB Interface

Specifications

82001I-E	Starting Watts	2200	Noise Level	53 dBA @ 7m
	Max Watts	2000	Start Type	Manual
	Rated Watts	1600	Low Oil Shut-off	Automatic
	AC Load	1 x 240V 13A (UK) 1 x 220V 16 Amp (EU)	Dimensions (L*W*H)	52 x 33 x 43 cm
	Engine	80cc Champion OHV	Weight (Kg)	19.6
	Fuel Capacity	4.1 Litres	Operation capacity (hr)	11 Hrs @ 25% load
	Oil Capacity	0.38 Litres	Parallel Connectivity	Yes
	Voltmeter	Yes	Cold Start	Yes