


3300 WATT INVERTER DUAL FUEL




- Petrol**
✓
- LPG**
✓
- Silent**
✓

3 YEAR WARRANTY



- Product Code:**  73001I-DF
Noise Level: 59 dBA @ 7m
Max AC output: 3300 / 3000 (LPG) Watts
Running Watts: 3200 / 2880 (LPG) Watts
Warranty: 3 Year
Suitable for:
- ✓ Computers
 - ✓ Small appliances
 - ✓ Household items



The Champion Power Equipment 73001I-DF portable dual fuel inverter petrol generator is powered by a 171cc Champion single cylinder, 4-stroke OHV engine that produces 3300 max watts.

Features a delay stop, allowing equipment to stop running or power down without any 'surge' thus protecting sensitive equipment. Another outstanding feature is the peak current capability. The unique design has a special peak current of 15.8amp allowing equipment to start up without tripping or overloading the generator especially running A/C units or similar.

This unit can run up to 8 hours on petrol and 16 hours on Propane (Based on 19kg bottle). Equipped with a low oil shut-off sensor & designed for long life and easy maintenance.

- Includes:
- 12v DC Battery Charging Cable
 - Oil funnel & Spark plug socket
 - Dual USB Interface
 - Propane Gas Pipe & Gas Valve

Specifications

Starting Watts	3500 / 3150 LPG	Recommended Oil	SAE 10w-30
Max Watts	3300 / 3000 LPG	Start Type	Electric start & manual
Rated Watts	3200 / 2880 LPG	Low Oil Shut-off	Automatic
AC Load	2 x 240v 13amp	Portability	Handle & Wheels
Phase	Single	Overload Protection	Automatic
Frequency	50 Hz	Choke Type	Automatic
Engine	171cc Champion OHV	Noise Level	59 dBA @ 7m
RPM	Automatic (based on load)	Dimensions (L*W*H)	69 x 49 x 50.5 cm
Fuel Capacity	6 Litres	Weight (Kg)	51
Oil Capacity	0.6 Litres	Operation capacity (hr)	8 Hrs / 16 Hrs (19kg LPG Bottle)