


# 3100 WATT INVERTER PREMIER



- Petrol**  
✓
- Silent**  
✓

**Product Code:**  73001I-P.  
**Noise Level:** 58 dBA @ 7m  
**Max AC output:** 3100 watts  
**Certification:** EC Approved  
**Warranty:** 3 Year  
**Suitable for:**

- ✓ Computer
- ✓ Power tools
- ✓ Lighting units
- ✓ Camping equipment etc.



This is our Champion signature Inverter generator loaded with optional extras including the Wireless Remote Start and USB interface powered by a 3 kilowatt engine.

The 73001I-P portable inverter petrol generator is powered by a 171cc Champion single cylinder, 4-stroke OHV engine that produces 3100 max watts.

With a 6 litre fuel tank this unit can run up to 8 hours at 25% load. Our OHV engine is equipped with a low oil shut-off sensor & is designed for long life & easy maintenance. It contains true sine wave inverter technology making it safe to power all of your sensitive electronic devices.

Features:

- Economy mode to save fuel
- Built-in Handle and Wheel Kit & Parallel capability

Includes:

- 12V DC Charging Cable, Oil funnel & Spark plug socket
- **Wireless remote start**
- **Dual USB Interface**

## Specifications

<b>Starting Watts</b>	3500	<b>Recommended Oil</b>	SAE 10w-30
<b>Max Watts</b>	3100	<b>Start Type</b>	Electric key start , remote start & recoil
<b>Rated Watts</b>	2800	<b>Low Oil Shut-off</b>	Automatic
<b>AC Load</b>	2 x 240v	<b>Portability</b>	Built-in handle & wheels
<b>DC Output</b>	12V/8.3A	<b>Choke Type</b>	Automatic
<b>Phase</b>	Single	<b>Noise Level</b>	58 dBA @ 7m
<b>Frequency</b>	50 Hz	<b>Dimensions (L*W*H)</b>	69 x 49 x 50.5 cm
<b>Engine</b>	171cc Champion OHV	<b>Weight (Kg)</b>	43
<b>Overload Protection</b>	Automatic	<b>Emissions</b>	EC Approved
<b>RPM</b>	Automatic (based on load)	<b>Operation capacity (hr)</b>	8 hrs at 25% load
<b>Fuel Capacity</b>	6 Litres	<b>Oil Capacity</b>	0.6 Litres